

## DNO reversing modification

This modification allows the DNO to change from ahead to reverse without the need to reduce the speed pot to zero. This is the same as the old VTX behaviour.

1] Gently scrape off the green PCB coating around the hole in the PCB here

2] Bend the legs of a 10uF 50V electrolytic capacitor as shown. The negative leg is on the left side as shown here

3] Using a fine soldering iron, solder the capacitor into place

4] Secure the capacitor to the PCB with hot melt glue or epoxy

